

Modelling the EAH Data Compression Algorithm using Graph Theory *

Dragoş N. Trincă (dragost@infoiasi.ro)

Faculty of Computer Science, "Al.I.Cuza" University, 700483 Iasi, Romania

Abstract. Adaptive codes associate variable-length codewords to symbols being encoded depending on the previous symbols in the input data string. This class of codes has been introduced in [9] as a new class of non-standard variable-length codes. New algorithms for data compression, based on adaptive codes of order one, have been presented in [10], where we have behaviorally shown that for a large class of input data strings, these algorithms substantially outperform the Lempel-Ziv universal data compression algorithm [18]. EAH has been introduced in [11], as an improved generalization of these algorithms. In this paper, we present a translation of the EAH algorithm into the graph theory.

Keywords: algorithms, coding theory, data compression, graph theory

1. Introduction

New algorithms for data compression, based on adaptive codes of order one [9], have been presented in [10], where we have behaviorally shown that for a large class of input data strings, these algorithms substantially outperform the well-known Lempel-Ziv universal data compression algorithm [18].

EAH (Encoder based both on Adaptive codes and the Huffman algorithm) has been proposed in [11], as an improved and generalized version of the algorithms presented in [10]. The work carried out so far [10, 11] has behaviorally proved that EAH is a very promising data compression algorithm, as one can remark again in the examples presented in the following sections. In this paper, we translate the EAH encoder, as well as some of the results obtained so far, into the graph theory.

In the remainder of this section, we recall the basic notions and notations used throughout the paper. We denote by $|S|$ the *cardinality* of the set S ; if x is a string of finite length, then $|x|$ denotes the length of x . The *empty word* is denoted by λ . Let us denote by Δ^* the set $\bigcup_{n=0}^{\infty} \Delta^n$ and by Δ^+ the set $\bigcup_{n=1}^{\infty} \Delta^n$. Also, denote by $\Delta^{\leq n}$ the set $\bigcup_{i=0}^n \Delta^i$ and by $\Delta^{\geq n}$ the set $\bigcup_{i=n}^{\infty} \Delta^i$, where Δ^0 denotes the set $\{\lambda\}$. $\mathbb{N}$ denotes the set of natural numbers, and $\mathbb{N}^* = \mathbb{N} - \{0\}$.

* The research reported in this paper was partially supported by CNCSIS grant 632/2004.



Let X be a finite and nonempty subset of Δ^+ , and $w \in \Delta^+$. A *decomposition* of w over X is any sequence of words $u_1, u_2, \dots, u_h$ with $u_i \in X$, $1 \leq i \leq h$, such that $w = u_1 u_2 \dots u_h$. A *code* over Δ is any nonempty set $C \subseteq \Delta^+$ such that each word $w \in \Delta^+$ has at most one decomposition over C . A *prefix code* over Δ is any code C over Δ such that no word in C is proper prefix of another word in C .

2. Adaptive Codes: A Short Review

The aim of this section is to briefly review some basic definitions, results, and notations directly related to adaptive codes.

DEFINITION 1. Let Σ, Δ be alphabets. A function $c : \Sigma \times \Sigma^{\leq n} \rightarrow \Delta^+$, $n \geq 1$, is called *adaptive code of order n* if its unique homomorphic extension $\bar{c} : \Sigma^* \rightarrow \Delta^*$, defined by:

- $\bar{c}(\lambda) = \lambda$
- $\bar{c}(\sigma_1 \sigma_2 \dots \sigma_m) = c(\sigma_1, \lambda) c(\sigma_2, \sigma_1) \dots c(\sigma_{n-1}, \sigma_1 \sigma_2 \dots \sigma_{n-2})$
 $c(\sigma_n, \sigma_1 \sigma_2 \dots \sigma_{n-1}) c(\sigma_{n+1}, \sigma_1 \sigma_2 \dots \sigma_n) c(\sigma_{n+2}, \sigma_2 \sigma_3 \dots \sigma_{n+1})$
 $c(\sigma_{n+3}, \sigma_3 \sigma_4 \dots \sigma_{n+2}) \dots c(\sigma_m, \sigma_{m-n} \sigma_{m-n+1} \dots \sigma_{m-1})$

for all $\sigma_1 \sigma_2 \dots \sigma_m \in \Sigma^+$, is injective.

As specified by the definition above, an adaptive code of order n associates variable-length codewords to symbols being encoded depending on the previous n symbols in the input data string.

EXAMPLE 1. Let us consider $\Sigma = \{a, b, c\}$ and $\Delta = \{0, 1\}$ two alphabets, and $c : \Sigma \times \Sigma^{\leq 2} \rightarrow \Delta^+$ a function constructed by the following table. One can easily verify that $\bar{c}$ is injective, and according to DEF. 1, c is an adaptive code of order two.

Table I. An adaptive code of order two.

$\Sigma \setminus \Sigma^{\leq 2}$	a	b	c	aa	ab	ac	ba	bb	bc	ca	cb	cc	λ
a	00	11	10	00	11	10	01	10	11	11	11	00	00
b	10	00	11	11	01	00	00	11	01	10	00	10	11
c	11	01	00	10	00	11	11	00	00	00	10	11	10

Let $x = abacca \in \Sigma^+$ be an input data string. Using the definition above, we encode x by:

$$\bar{c}(x) = c(a, \lambda) c(b, a) c(a, ab) c(c, ba) c(c, ac) c(a, cc) = 001011111100.$$

Let $c : \Sigma \times \Sigma^{\leq n} \rightarrow \Delta^+$ be an adaptive code of order n , $n \geq 1$. We denote by $\mathcal{C}_{c, \sigma_1 \sigma_2 \dots \sigma_h}$ the set $\{c(\sigma, \sigma_1 \sigma_2 \dots \sigma_h) \mid \sigma \in \Sigma\}$, for all $\sigma_1 \sigma_2 \dots \sigma_h \in \Sigma^{\leq n} - \{\lambda\}$, and by $\mathcal{C}_{c, \lambda}$ the set $\{c(\sigma, \lambda) \mid \sigma \in \Sigma\}$. We write $\mathcal{C}_{\sigma_1 \sigma_2 \dots \sigma_h}$ instead of $\mathcal{C}_{c, \sigma_1 \sigma_2 \dots \sigma_h}$, and $\mathcal{C}_\lambda$ instead of $\mathcal{C}_{c, \lambda}$ whenever there is no confusion.

Let us denote by $\mathcal{AC}(\Sigma, \Delta, n)$ the set $\{c : \Sigma \times \Sigma^{\leq n} \rightarrow \Delta^+ \mid c \text{ is an adaptive code of order } n\}$. The proof of the following theorem can be found in [9].

THEOREM 1. *Let Σ and Δ be two alphabets, and $c : \Sigma \times \Sigma^{\leq n} \rightarrow \Delta^+$ a function. If $\mathcal{C}_u$ is prefix code, for all $u \in \Sigma^{\leq n}$, then $c \in \mathcal{AC}(\Sigma, \Delta, n)$.*

3. Modelling the EAH Encoder using the Graph Theory

This section focuses on modelling some of the results obtained so far, as well as the EAH data compression algorithm [11], using the graph theory.

DEFINITION 2. *Let Σ be an alphabet, and $w = u_1 u_2 \dots u_h \in \Sigma^+$, where $u_i \in \Sigma$ for all i , $1 \leq i \leq h$. The adaptive graph of order n associated to w is a 3-tuple $G_n(w) = (V, E, f)$, where $f : E \rightarrow \mathbb{N} \times \{0, 1\}^*$ is a function, and (V, E) is a directed graph defined as below.*

- $V = Vbase \cup Vaux$.
- $E = Ebase \cup Eaux$.
- $Vbase = \begin{cases} \emptyset & \text{if } h \leq n. \\ \{u_j u_{j+1} \dots u_{j+n-1} \mid 1 \leq j \leq h-n\} \\ \cup \{u_j \mid n+1 \leq j \leq h\} & \text{if } h > n. \end{cases}$
- $Vaux = \begin{cases} \emptyset & \text{if } n \geq 2. \\ \{u_j \text{-} aux \mid j \leq h-1 \text{ and } u_j = u_{j+1}\} & \text{if } n = 1. \end{cases}$
- $Ebase = \begin{cases} \emptyset & \text{if } h \leq n. \\ \{(u_j \dots u_{j+n-1}, u_{j+n}) \mid j \geq 1\} & \text{if } h > n \text{ and } n \geq 2. \\ \{(u_j, u_{j+1}) \mid u_j \neq u_{j+1}\} & \text{if } h > n \text{ and } n = 1. \end{cases}$
- $Eaux = \begin{cases} \emptyset & \text{if } h \leq n. \\ \{(u_j, u_j \text{-} aux) \mid u_j = u_{j+1}\} \\ \cup \{(u_j \text{-} aux, u_j) \mid u_j = u_{j+1}\} & \text{if } h > n = 1. \\ \{(u_j, u_{j-n+1} \dots u_j) \mid n+1 \leq j \leq h-1\} & \text{if } h > n \geq 2. \end{cases}$

For all $e \in E$, if $f(e) = (x, y)$ then x is defined as follows.

$$x = \begin{cases} |\{i \mid u_i \dots u_{i+n} = u_j \dots u_{j+n}\}| & \text{if } e = (u_j \dots u_{j+n-1}, u_{j+n}). \\ |\{i \mid u_i = u_{i+1} = u_j\}| & \text{if } e = (u_j, u_{j_aux}). \\ 0 & \text{if } e = (u_{j_aux}, u_j). \\ 0 & \text{if } e = (u_j, u_{j-n+1} \dots u_j). \end{cases}$$

Let us introduce some basic notations used throughout the section, and then give a few examples of adaptive graphs. Let Σ be an alphabet, $w \in \Sigma^+$, $G_n(w) = (V, E, f)$, and $x \in V = Vbase \cup Vaux$.

- $input_b^{G_n(w)}(x) = \{(y, x) \mid y \in Vbase\}$.
- $input_a^{G_n(w)}(x) = \{(y, x) \mid y \in Vaux\}$.
- $output_b^{G_n(w)}(x) = \{(x, y) \mid y \in Vbase\}$.
- $output_a^{G_n(w)}(x) = \{(x, y) \mid y \in Vaux\}$.
- $i_b^{G_n(w)}(x) = |input_b^{G_n(w)}(x)|$.
- $o_b^{G_n(w)}(x) = |output_b^{G_n(w)}(x)|$.
- $i_a^{G_n(w)}(x) = |input_a^{G_n(w)}(x)|$.
- $o_a^{G_n(w)}(x) = |output_a^{G_n(w)}(x)|$.

EXAMPLE 2. Let $\Sigma = \{a, b, c, d\}$ be an alphabet, $w = abccdbbab \in \Sigma^+$, and $G_1(w) = (V, E, f)$ the adaptive graph of order one associated to w . It is easy to verify that we get the following results.

- $V = \{a, b, c, d, c_aux, b_aux\}$.
- $E = \{(a, b), (b, a), (b, b_aux), (b_aux, b), (b, c), (c, c_aux), (c, d), (c_aux, c), (d, b)\}$.




Figure 1. $G_1(abccdbbab)$.

Let $U = (u_1, u_2, \dots, u_k)$ be a k -tuple. We denote by $U.i$ the i -th component of U , that is, $u_i = U.i$, for all i , $1 \leq i \leq k$. The 0-tuple is denoted by $()$. The length of a tuple U is denoted by $Len(U)$. If $V = (v_1, v_2, \dots, v_b)$, $M = (m_1, m_2, \dots, m_r, U)$, $N = (n_1, n_2, \dots, n_s, V)$, $P = (p_1, \dots, p_{i-1}, p_i, p_{i+1}, \dots, p_t)$ are tuples, and q is an element or a tuple, then we define $P \triangleleft q$, $P \triangleright i$, $U \triangle V$, and $M \diamond N$ by:

- $P \triangleleft q = (p_1, \dots, p_t, q)$
- $P \triangleright i = (p_1, \dots, p_{i-1}, p_{i+1}, \dots, p_t)$
- $U \triangle V = (u_1, u_2, \dots, u_k, v_1, v_2, \dots, v_b)$
- $M \diamond N = (m_1 + n_1, m_2 + 1, \dots, m_r + 1, n_2 + 1, \dots, n_s + 1, U \triangle V)$

where m_i, n_j are integers, $1 \leq i \leq r$ and $1 \leq j \leq s$. Let us denote by Huffman the Huffman algorithm, which gets as input a tuple $(f_1, \dots, f_k)$ of integers, and returns a tuple $((c_1, l_1), \dots, (c_k, l_k))$, where c_i is the codeword associated to the symbol with the frequency f_i , and l_i is the length of c_i for all i , $1 \leq i \leq k$.

```

Huffman(tuple  $\mathcal{F} = (f_1, \dots, f_k)$ , where  $k \geq 1$ )
1.  $\mathcal{L} := ((f_1, 0, (1)), \dots, (f_k, 0, (k)))$ ; Let  $\mathcal{V} = (\lambda, \lambda, \dots, \lambda)$  be a  $k$ -tuple;
2. if  $k = 1$  then  $\mathcal{V}.1 := 0$ ;
3. while  $Len(\mathcal{L}) > 1$  do
  begin
    3.1. Let  $i < j$  be such that  $1 \leq i, j \leq Len(\mathcal{L})$  and  $\mathcal{L}.i.1, \mathcal{L}.j.1$  are
        the smallest elements of the set  $\{\mathcal{L}.q.1 \mid 1 \leq q \leq Len(\mathcal{L})\}$ ;
    3.2.  $First := \{\mathcal{L}.i.Len(\mathcal{L}.i).r \mid 1 \leq r \leq Len(\mathcal{L}.i.Len(\mathcal{L}.i))\}$ ;
    3.3.  $Second := \{\mathcal{L}.j.Len(\mathcal{L}.j).r \mid 1 \leq r \leq Len(\mathcal{L}.j.Len(\mathcal{L}.j))\}$ ;
    3.4. for each  $x \in First$  do  $\mathcal{V}.x := 0 \cdot \mathcal{V}.x$ ;
    3.5. for each  $x \in Second$  do  $\mathcal{V}.x := 1 \cdot \mathcal{V}.x$ ;
    3.6.  $\mathcal{U} := \mathcal{L}.i \diamond \mathcal{L}.j$ ;  $\mathcal{L} := \mathcal{L} \triangleright j$ ;  $\mathcal{L} := \mathcal{L} \triangleright i$ ;  $\mathcal{L} := \mathcal{L} \triangleleft \mathcal{U}$ ;
  end
4. return  $((\mathcal{V}.1, |\mathcal{V}.1|), \dots, (\mathcal{V}.k, |\mathcal{V}.k|))$ ;

```

Figure 2. The Huffman algorithm.

Let $\Sigma = \{\sigma_0, \sigma_1, \dots, \sigma_{m-1}\}$ be an alphabet, and $m \in \{1, 2, \dots, 256\}$. Let us explain the idea of our algorithm, denoted by $EAHn$. For example, let $w = w_1 w_2 \dots w_h$ be a string over Σ . We encode w by a 5-tuple $U = (A, B, C, D, E)$, where $A, B, C, D, E \in \{0, 1\}^+$ are constructed as follows.

1. $EAHn(w).1 = A$. Let $Idx : \Sigma \rightarrow \{0, 1, \dots, m-1\}$ be a function which gets as input a symbol $\sigma \in \Sigma$ and outputs an index i such that $\sigma = \sigma_i$. If $h \geq n$, then $A = b10b2(Idx(w_1)) \dots b10b2(Idx(w_n))$, that is, A is the conversion of the sequence $Idx(w_1), \dots, Idx(w_n)$ from base 10 to base 2, and $|A| = n * \lceil \log_2 m \rceil$. Otherwise, if $h < n$,

then we consider $A = b10b2(Idx(w_1)) \dots b10b2(Idx(w_h))$, that is, A is the conversion of $Idx(w_1), \dots, Idx(w_h)$ from base 10 to base 2, and $|A| = h * \lceil \log_2 m \rceil$.

2. $EAHn(w).2 = B = B_0 B_1 \dots B_{m^n-1}$, where $B_j \in \{0, 1\}$ is defined by:

$$B_j = \begin{cases} 1 & \text{if } \exists i \in \{0, \dots, m-1\} \text{ and } \exists k \text{ such that } w_k \dots w_{k+n} \\ & = Idx^{-1}(b10(j, m).1) \dots Idx^{-1}(b10(j, m).n) \cdot \sigma_i. \\ 0 & \text{otherwise.} \end{cases}$$

for all j , $0 \leq j \leq m^n - 1$, and $b10(j, m)$ is a tuple of length n denoting the conversion of j from base 10 to base m , such that $Len(b10(j, m)) = n$ and $b10(j, m).i$ is the i -th digit (from left to right) of this conversion.

3. $EAHn(w).3 = C = C_0 C_1 \dots C_{m-1}$, where $C_i = C_i^0 C_i^1 \dots C_i^{m^n-1}$, for all i , $0 \leq i \leq m-1$, and $C_i^j \in \{0, 1, \lambda\}$ is defined by:

$$C_i^j = \begin{cases} 1 & \text{if } B_j = 1 \text{ and } \exists k \in \{1, \dots, h-n\} \text{ such that } w_k \dots w_{k+n} \\ & = Idx^{-1}(b10(j, m).1) \dots Idx^{-1}(b10(j, m).n) \cdot \sigma_i. \\ 0 & \text{if } B_j = 1 \text{ and } \nexists k \in \{1, \dots, h-n\} \text{ such that } w_k \dots w_{k+n} \\ & = Idx^{-1}(b10(j, m).1) \dots Idx^{-1}(b10(j, m).n) \cdot \sigma_i. \\ \lambda & \text{if } B_j = 0. \end{cases}$$

for all j , $0 \leq j \leq m^n - 1$. It is clear that $|C| = m * |\{k \mid B_k = 1\}|$.

4. $EAHn(w).4 = D = D_0 D_1 \dots D_{m-1}$, where $D_i = D_i^0 D_i^1 \dots D_i^{m^n-1}$ for all i , $0 \leq i \leq m-1$, and $D_i^j \in \{0, 1\}^*$ is defined by:

$$D_i^j = \begin{cases} Mb10b2(Freq(\sigma_i, j)) & \text{if } C_i^j = 1. \\ \lambda & \text{if } C_i^j \neq 1. \end{cases}$$

where $Freq(\sigma_i, j) = |\{k \mid w_k \dots w_{k+n} = \sigma_{b10(j, m).1} \dots \sigma_{b10(j, m).n} \sigma_i\}|$. Let us denote by *Marked* the set $\{(i, j) \mid C_i^j = 1\}$. The greatest element of the set $\{|b10b2(Freq(\sigma_i, j))| \mid (i, j) \in \text{Marked}\}$ is denoted by *Max*. Then, $Mb10b2(Freq(\sigma_i, j))$ is defined by:

$$Mb10b2(Freq(\sigma_i, j)) = \underbrace{00 \dots 0}_{t(i, j)} b10b2(Freq(\sigma_i, j))$$

where $t(i, j) = \text{Max} - |b10b2(Freq(\sigma_i, j))|$.

5. $EAHn(w).5 = E$ denotes the compression of w using A, B, C, D , adaptive codes of order n , and the Huffman algorithm.

```

EAHn(string  $w = w_1w_2 \dots w_h \in \Sigma^+$ , where  $w_i \in \Sigma$  for all  $i$ ,  $1 \leq i \leq h$ )
1.  $G_n(w) := (\emptyset, \emptyset, f)$ ;  $A := \lambda$ ;  $B := \lambda$ ;  $C := \lambda$ ;  $D := \lambda$ ;  $E := \lambda$ ;
2. if  $h > n$  then
  begin
  2.1. for  $j = 1$  to  $h - n$  do  $G_n(w).1 := G_n(w).1 \cup \{w_jw_{j+1} \dots w_{j+n-1}\}$ ;
  2.2. for  $j = n + 1$  to  $h$  do  $G_n(w).1 := G_n(w).1 \cup \{w_j\}$ ;
  2.3. for  $j = 1$  to  $h - n$  do  $G_n(w).2 := G_n(w).2 \cup \{(w_j \dots w_{j+n-1}, w_{j+n})\}$ ;
  2.4. if  $n = 1$  then
    begin
    2.4.1. for  $j = 1$  to  $h - 1$  do
    2.4.2. if  $w_j = w_{j+1}$  then  $G_n(w).2 := G_n(w).2 \cup \{(w_j, w_j \text{aux}), (w_j \text{aux}, w_j)\}$ ;
    end
    2.5. else for  $j = n + 1$  to  $h - 1$  do  $G_n(w).2 := G_n(w).2 \cup \{(w_j, w_{j-n+1} \dots w_j)\}$ ;
    end
  3. if  $n = 1$  then
  4. for  $j = 1$  to  $h - 1$  do
  5. if  $w_j = w_{j+1}$  then  $G_n(w).1 := G_n(w).1 \cup \{w_j \text{aux}\}$ ;
  6. for each  $e \in G_n(w).2$  do  $f(e) := (0, \lambda)$ ;
  7. for  $i = n + 1$  to  $h$  do
    begin
    7.1. if  $n = 1$  and  $w_{i-1} = w_i$  then let  $e \in G_n(w).2$  be  $(w_i, w_i \text{aux})$ ;
    7.2. else let  $e \in G_n(w).2$  be  $(w_{i-n} \dots w_{i-1}, w_i)$ ;
    7.3.  $f(e).1 := f(e).1 + 1$ ;
    end
    8. for each  $w_jw_{j+1} \dots w_{j+n-1} \in Vbase$  do
      begin
      8.1.  $fu := ()$ ;  $count := 0$ ;
      8.2.  $tuple := Sorted(output_b^{G_n(w)}(w_j \dots w_{j+n-1}) \cup output_a^{G_n(w)}(w_j \dots w_{j+n-1}))$ ;
      8.3. for  $i = 1$  to  $Len(tuple)$  do  $fu := fu \triangleleft f(tuple.i).1$ ;
      8.4. for  $i = 1$  to  $Len(tuple)$  do
        begin
        8.4.1.  $count := count + 1$ ;
        8.4.2.  $f(tuple.i).2 := Huffman(fu).count.1$ ;
        end
      end
    9.  $A := b10b2(Idx(w_1)) \dots b10b2(Idx(w_{min(h,n)}))$ ;
    10. for  $j = 0$  to  $m^n - 1$  do
    11. if  $(\sigma_{b10(j,m).1} \dots \sigma_{b10(j,m).n}, \sigma_i) \in G_n(w).2$  then  $B := B \cdot 1$ ; else  $B := B \cdot 0$ ;
    12. for  $i = 0$  to  $m - 1$  do
    13. for  $j = 0$  to  $m^n - 1$  do
    14. if  $B_j = 1$  then
      begin
      14.1. if  $n = 1$  and  $i = j$  then  $e := (\sigma_i, \sigma_i \text{aux})$ ;
      14.2. else  $e := (\sigma_{b10(j,m).1} \dots \sigma_{b10(j,m).n}, \sigma_i)$ ;
      14.3. if  $e \in G_n(w).2$  then
      14.4. begin  $C := C \cdot 1$ ;  $D := D \cdot Mb10b2(f(e).1)$ ; end else  $C := C \cdot 0$ ;
      end
    15. for  $i = n + 1$  to  $h$  do
      begin
      15.1. if  $n = 1$  and  $w_{i-1} = w_i$  then  $e := (w_i, w_i \text{aux})$ ; else  $e := (w_{i-n} \dots w_{i-1}, w_i)$ ;
      15.2.  $E := E \cdot f(e).2$ ;
      end
    16. return  $(A, B, C, D, E)$ ;

```

Figure 3. The EAH data compression algorithm.

If S is a set of edges, then $\text{Sorted}(S)$ denotes a tuple U which contains the elements of S , but sorted with a certain algorithm (the algorithm is not important here, but must be fixed).

Let w be an input data string. We denote by $H(w)$ the encoding of w using the Huffman algorithm, and by $LZ(w)$ the encoding of w using the Lempel-Ziv data compression algorithm [18]. Let us consider the following notations.

- $LH(w) = |H(w)|$.
- $LLZ(w) = |LZ(w)|$.
- $LEAHn(w) = \sum_{i=1}^5 |\text{EAHn}(w).i|$.

EXAMPLE 3. Let $\Sigma = \{a, b, c, d, e\}$ be an alphabet, and w a string of length 200 over Σ , given as below (between brackets).

$w = [abedcababedccabedcedcababedcedcccabedcabedcedccababedcabedccccedccedccedcababedcabedcedccedcababedccababedcedccccedcabedcabedccccedcccabedccccedccabedccccabedccababedcababedcedccabedcababedced]$.

Applying EAH1 to the string w , we get the following adaptive graph of order one.




Figure 4. $G_1(w)$.

It is easy to verify that we obtain:

$$LH(w) = 462 \qquad LEAH1(w) = 310 \qquad LLZ(w) = 388$$

which shows that in this case EAH1 substantially outperforms the well-known Lempel-Ziv universal data compression algorithm [18].

4. Conclusions and Further Work

Adaptive codes associate variable-length codewords to symbols being encoded depending on the previous symbols in the input data string.

This class of codes has been introduced in [9] as a new class of non-standard variable-length codes. New algorithms for data compression based on adaptive codes of order one, have been presented in [10], where we have behaviorally shown that for a large class of input data strings, these algorithms substantially outperform the Lempel-Ziv universal data compression algorithm [18].

The EAH encoder has been proposed in [11], as an improved generalization of these algorithms. The work carried out so far [10, 11] has behaviorally shown that EAH is a very promising data compression algorithm. In this paper, we presented a translation of the EAH algorithm into the graph theory. Further work in this area will focus on finding new improvements for the EAH algorithm, as well as new algorithms for data compression based on adaptive codes.

References

1. Bell, T. C., Cleary, J. G., I. H. Witten. *Text Compression*. Prentice Hall, 1990.
2. Berstel, J., D. Perrin. *Theory of Codes*. Academic Press, 1985.
3. Nelson, M., J. Gailly. *The Data Compression Book*. M&T Books, New York, NY, 1996, 2nd edition.
4. Pless, V. S., W. C. Huffman (Eds.). *Handbook of Coding Theory* (2 volumes). Elsevier, 1998.
5. Rozenberg, G., A. Salomaa (Eds.). *Handbook of Formal Languages*. Springer-Verlag, 1997.
6. Salomaa, A. *Jewels of Formal Language Theory*. Computer Science Press, 1981.
7. Salomon, D. *Data Compression. The Complete Reference*. Springer-Verlag, 1998.
8. Storer, J. A. *Data Compression: Methods and Theory*. Computer Science Press, Rockville, MD, 1988.
9. Trincă, D. Adaptive Codes: A New Class of Non-standard Variable-length Codes. (to appear in *Romanian Journal of Information Science and Technology*)
10. Trincă, D. Towards New Algorithms for Data Compression using Adaptive Codes. In *Proceedings of the 5th International Conference on Information Technology: Coding and Computing*, Las Vegas, Nevada, USA, 2004, volume 1, pages 767-772. IEEE Computer Society.
11. Trincă, D. EAH: A New Encoder based on Adaptive Codes. Outperforming the LZ77 Encoder. manuscript, 2004.
12. Trincă, D. Special Cases of Encodings by Generalized Adaptive Codes. manuscript, 2004.
13. Trincă, D. Meta-EAH: An Adaptive Encoder based on Adaptive Codes. Moving between Adaptive Mechanisms. In *Proceedings of the 3rd International Symposium on Information and Communication Technologies*, Las Vegas, Nevada, USA, 2004, to appear. ACM Digital Library.
14. Trincă, D. Translating the EAH Data Compression Algorithm into Automata Theory. manuscript, 2004.

15. Trincă, D. Computing the Entropy Bounds of the EAH Data Compression Algorithm. manuscript, 2004.
16. Țiplea, F. L., Mäkinen, E., C. Enea. SE-Systems, Timing Mechanisms and Time-Varying Codes. *International Journal of Computer Mathematics*, 79(10):1083–1091, 2002.
17. Țiplea, F. L., Mäkinen, E., Trincă, D., C. Enea. Characterization Results for Time-Varying Codes. *Fundamenta Informaticae*, 53(2):185–198, 2002.
18. Ziv, J., A. Lempel. Compression of individual sequences via variable-rate coding. *IEEE Transactions on Information Theory*, vol. (IT-24):530–536, 1978.